

TWO-CIRCUIT MONORAIL

Remote Transformer-2x150W Mag 12v



DESCRIPTION

This remote magnetic transformer converts standard 120 volt line-voltage to 12 volts, providing the necessary voltage for powering a Two-Circuit MonoRail low-voltage lighting system. Each transformer includes fast-acting secondary circuit breakers that will safely turn the system off should a short occur. Once the short has been removed the breakers can be reset. Transformer powers lamp totaling up to 300 watts.



INSTALLATION

This transformer must be installed in a remote but accessible location (such as above the ceiling or in a closet). To simplify installation the transformer should be located no more than 20' from the run or power feed. The electrician will need to supply the proper gauge conductor from the transformer to the power feed location based on distance (see Low-Voltage Wire Size Table, below).

OTHER

12 volt output transformers require the use of 12 volt lamps. Use with a single-feed Two-Circuit canopy or other power feed option (sold separately).

LOW-VOLTAGE WIRE SIZE TABLE

Use to determine the correct THHN wire size for a recommended 3 percent drop in voltage at the specified wattage. The length shown is the length of wire from the transformer to the power feed.

12 Volt	5 ft.	6-15 ft.	16-20 ft.	21-40 ft.	41-60 ft.	61-90 ft.
150 Watt	#12 GA	#8 GA	#6 GA	#4 GA	#2 GA	#1 GA

WEIGHT

24.2lb / 10.98kg ±

ORDERING INFORMATION

700AT2X150T VOLTAGE

120V IN/12V OUT

As a general rule when using LED fixtures we do not recommend using greater than 70% of specified maximum wattage on the transformer due to inrush current. For assistance, please contact our technical support department.



TECH LIGHTING®

7400 Linder Avenue
Skokie, Illinois 60077

T 847.410.4400
F 847.410.4500

Tech Lighting, L.L.C.

700AT2X150T _____

FIXTURE TYPE: _____

JOB NAME: _____

NOTES: _____



©2014 Tech Lighting, L.L.C. All Rights Reserved. The "Tech Lighting" graphic is a registered trademark of Tech Lighting, L.L.C. Tech Lighting reserves the right to change specifications for product improvements without notification.