


# Recessed Can Adapter



Shown approx. 10% actual size.



## DESCRIPTION

Used to retrofit existing recessed downlights for use with FreeJack heads and pendants of up to 75 watts. Includes 12 volt, 75 watt electronic transformer. Each FreeJack element can be used up to its specified wattage (see element and accessory for details).

## INSTALLATION

Mounts to any recessed can that is 6-1/4" to 6-1/2" in diameter and has "C" shaped hooks on the inside can wall. Transformer (included) fits in recessed can.

ETL listed for use with the following recessed canopies: Juno® IC2, IC22, TC2, and TC2R; Halo® H7T and H7RT; Cooper® H27RT; Capri (Thomas) Lighting® PR75ASIC/TPR75ASIC/DY6431; Progress Lighting® P7TG, P8-TG, P-8TG and PIO8-TG.

Tech Lighting is not affiliated with, nor is it endorsed by, any of the companies listed above. Tech Lighting does not distribute any of the products listed above.

## FINISH

Antique bronze, chrome, satin nickel, white.

## REQUIRED USAGE

Any 12 Volt FreeJack pendant or head (sold separately).

## DIMMING

Dimmable with standard incandescent dimmer.

## WEIGHT

1.70 lb./0.77 kg. ±

## ORDERING INFORMATION

### 700FJRCAD

#### FINISH

- Z ANTIQUE BRONZE
- C CHROME
- S SATIN NICKEL
- W WHITE



7400 Linder Avenue T 847.410.4400  
 Skokie, Illinois 60077 F 847.410.4500

www.techlighting.com

700FJRCAD \_\_\_\_\_

FIXTURE TYPE: \_\_\_\_\_

JOB NAME: \_\_\_\_\_

