


Surface Transformer

SINGLE-FEED, 12 VOLTS 150 WATTS



Shown approx. 20% actual size.



kl_srt15d_spec.pdf

DESCRIPTION

This single-feed surface transformer converts standard 120 volt line-voltage to 12 volts to provide the necessary voltage for powering a Kable Lite system. It can power lamps totaling up to 150 watts. The transformer is concealed inside a decorative housing with a fast-acting secondary circuit breaker that will safely turn off the system should a short occur. Once the short has been removed the breaker can be reset.

INSTALLATION

This product can mount to either a standard 4" square electrical box with round plaster ring or an octagon electrical box (not included).

DIMMING

Dimmable with a 600 watt low-voltage magnetic dimmer. The dimmer is placed on the line side of the transformer. (Consult dimmer manufacturer for specifics). This surface transformer includes a preinstalled debuzzing dimming coil to reduce audible noise when using a low-voltage dimmer.

FINISH

Chrome, satin nickel, black, white. Black and white finish have chrome feeds.

COMPATIBLE RIGID STANDOFFS

The shortest rigid standoff that can be used with this surface transformer is the 2.5" rigid post standoff (sold separately).

OPTIONS

This surface transformer may be plugged in with the addition of a Plug Option, a 16 foot cord with inline switch two feet from the plug (sold separately).

REQUIRED USAGE

12 volt transformers require the use of 12 volt lamps.

WEIGHT

7.20 lb./3.27 kg. ±

ORDERING INFORMATION

700SRT15D

FINISH

- C CHROME
- S SATIN NICKEL
- B BLACK
- W WHITE



7400 Linder Avenue T 847.410.4400
Skokie, Illinois 60077 F 847.410.4500

www.techlighting.com

700SRT15D _____

FIXTURE TYPE: _____

JOB NAME: _____

