

## Lighting Your Life Since 1970

Product Specifications - 3006CLBK					
Job Name:	Job Type:				
	1 "				
Quantity:	Comments				
[ ]					



## 3006CLBK

**Builder Cast 1-Light Outdoor Pole/Post Lantern** 

FinishGlass/ShadeProduct CategoryBlackClearOutdoor Pole/Post Mount

Lamping	
Number of Bulbs	1
Light Type	Incandescent
Bulb Type	MB
Max Bulb Wattage	100
Max Fixture Wattage	100
Rated Life	±2,500 Hours
Rated Lumens	±1,150
Color Temp	±2,700 K
Bulb(s)	Not Included
Light Up/Down	N/A
Beam Spread	N/A
CRI	N/A
Photo Cell Included	N/A
Ballast/Driver/Transformer	No

Standard

**Dimmable** 

Measurements	
Width	6.0"
Height	16.0"
Length	N/A
Extension	N/A
Back Plate Width	N/A
Back Plate Height	N/A
НСО	N/A
Min Overall Height	N/A
Max Overall Height	N/A
Hanging Weight	1.5 lbs
Height Adjustable	N/A
Slope	N/A
Chain Length	N/A
Wire Length	N/A
Canopy Width	N/A
Canopy Height	N/A
Canopy Length	N/A

	Shipping	
"	Carton Weight	1.5 lbs
"	Carton Width	7"
١	Carton Height	12"
١	Carton Length	7"
١	Carton Cubic Feet	0.35
١	Master Pack	6
١	Master Pack Weight	20.5 lbs
١	Master Pack Width	14.6"
١	Master Pack Height	13.0"
3	Master Pack Length	22.4"
١	Master Cubic Feet	2.46
١	UPS Shippable	Yes
١		

Certification		Other		Equivalents	
Safety Rating	Wet	UPC Code	783209300651	Incandescent Watts	N/A
Energy Star	No	Shades Included	N/A	Fluorescent Watts	N/A
CA Title 24	No	Crystals Included	N/A		
CA Title 20	No	Diffuser Included	N/A		
ADA	No	Conversion Kit	N/A		
Dark Sky	N/A	Material	Die Cast Aluminum		

Maxim Lighting International and all designs, logos and images © 2013 Maxim Lighting International. All Rights Reserved. Maxim Lighting International reserves the right, at any time, to make changes in the design and/or construction of the product including the discontinuation of product without prior notice. Color may vary from what is pictured above due to limitations inherent to photographic processes.

Always consult a qualified, licensed electrician before installation of any product weighing 35 pounds or more. We recommend that a qualified, licensed electrician do the installation. Always install to a mechanically sound structure.