


# 4" Round Flush Canopy



Shown approx. 35% actual size.



fj\_4rnd\_flush\_can\_spec.pdf

### DESCRIPTION

4" Round Flush Canopy with one FreeJack port. Use in conjunction with any FreeJack element to create a decorative ceiling fixture. Includes 12 or 24 volt, 75 watt electronic transformer. Each FreeJack element can be used up to its specified wattage (see element and accessory for details).

### INSTALLATION

This product can mount to either a 4" square electrical box with round plaster ring or an octagonal electrical box (not included). Transformer (included) fits in junction box. For ceiling or wall. If wall mounting, head should be no longer than 6".

### FINISH

Antique bronze, chrome, satin nickel, black, white.

### REQUIRED USAGE

Any 12 or 24 Volt FreeJack pendant or head (sold separately).

### DIMMING

120V IN/12V OUT and 120V IN/24V OUT dimmable with a standard incandescent dimmer (not included).  
277V IN/12V OUT dimmable with a compatible dimmer (not included).

### WEIGHT

0.80 lb./0.36 kg. ±

### ORDERING INFORMATION

700FJ4RF	FINISH	VOLTAGE
	Z ANTIQUE BRONZE	120V IN/12V OUT
	C CHROME	<b>024</b> 120V IN/24V OUT
	S SATIN NICKEL	<b>277</b> 277V IN/12V OUT
	B BLACK	
	W WHITE	



7400 Linder Avenue T 847.410.4400  
Skokie, Illinois 60077 F 847.410.4500

[www.techlighting.com](http://www.techlighting.com)

700FJ4RF \_\_\_\_\_

FIXTURE TYPE: \_\_\_\_\_

JOB NAME: \_\_\_\_\_

