

**FreeJack 4" Round Flush Canopy**



**DESCRIPTION**

Mounts to a standard 4" junction box with round plaster ring (provided by electrician). Electronic transformer (included) fits in junction box. One FreeJack port; for ceiling or wall.

**INSTALLATION**

This product can mount to either a 4" square electrical box with round plaster ring or an octagonal electrical box (not included). Transformer (included) fits in junction box. For ceiling or wall. If wall mounting, head should be no longer than 6".

**DIMMING**

120V IN/12V OUT and 120V IN/24V OUT dimmable with a standard incandescent dimmer (not included). 277V IN/12V OUT dimmable with a 277V incandescent dimmer (not included).


**OTHER INFORMATION**

For use with any 12 or 24 volt halogen FreeJack pendant or head (sold separately).

**WEIGHT**

0.8lb / 0.36kg

**ORDERING INFORMATION**



700FJ4RF FINISH	VOLTAGE
Z ANTIQUE BRONZE	120V IN/12V OUT
B BLACK	<b>024</b> 120V IN/24V OUT
C CHROME	<b>277</b> 277V IN/12V OUT
S SATIN NICKEL	
W WHITE	



**TECH LIGHTING®**  
 7400 Linder Avenue T 847.410.4400  
 Skokie, Illinois 60077 F 847.410.4500  
[www.techlighting.com](http://www.techlighting.com)

700FJ4RF \_\_\_\_\_

FIXTURE TYPE: \_\_\_\_\_

JOB NAME: \_\_\_\_\_

NOTES: \_\_\_\_\_  
 \_\_\_\_\_  
 \_\_\_\_\_