

Kable Lite Flush Transformer-60W LED



DESCRIPTION

This single-feed flush transformer converts standard 120 line-voltage to 12 volts to provide the necessary voltage for powering a Kable Lite low-voltage lighting system. It can power lamps totaling up to 60 watts. The transformer, concealed by a decorative canopy, fits in junction box and features a fast acting secondary circuit breaker that will safely turn the system off should a short occur. Once the short has been removed the unit can be reset by simply flipping the wall switch off and back on.

INSTALLATION

This product can mount to either a standard 4" square electrical box with round plaster ring or an octagon electrical box (not included).

DIMMING

Dimmable with a 600 watt low-voltage electronic dimmer. The dimmer is placed on the line side of the transformer. (Consult dimmer manufacturer for specifics).

OTHER INFORMATION

Black and white finish have chrome feeds. The shortest rigid standoff that can be used with this surface transformer is the 1" rigid post standoff (sold separately). 12 volt transformers require the use of 12 volt lamps.


WEIGHT

0.8lb / 0.36kg

ORDERING INFORMATION

700FRT60E FINISH

- B- BLACK LED
- C- CHROME LED
- S- SATIN NICKEL LED
- W- WHITE LED



TECH LIGHTING®

7400 Linder Avenue T 847.410.4400
 Skokie, Illinois 60077 F 847.410.4500

www.techlighting.com

700FRT60E _____

FIXTURE TYPE: _____

JOB NAME: _____

NOTES: _____

