


# Illuma-Flex Transformer Low Voltage

## Track



Finish			
	Brushed	Urban	Dimensions (Inches)
Catalog No.	Nickel	Bronze	A B



# **Specifications:**

#### <u>General</u>

- 300 watt 120 to 12 volt low profile electronic transformer
- Mounts anywhere along Illuma-Flex track sections
- Positive support and connection for the Flex track

### Mounting

- Ceiling mount over a standard 4" hexagonal outlet box (by others)
- Removal of bottom cap allows track to be slid into slot, cap is replaced and side thumb screws tightened for solid contact to track
- Mounting hardware included for attachment to a standard 4" hexagonal outlet box.

# **Electrical**

- Maximum loading is 300w, minimum loading is 50w
- LED Overload Indicator

## <u>Labeling</u>

UL-CUL listed

Progress Lighting Post Office Box 5704 Spartanburg, South Carolina 29304-5704