


CATALOG NUMBER	TYPE
PROJECT	

FLEXRAIL1 STRAIGHT RAIL

MODELS HM1-T



Ordering Matrix		
Model	Length	Finish
[]	[]	[]
HM1-T	4 8	PT BZ

Ordering Example (model number – length – finish) : HM1-T8-PT

Product Details	
Description:	Flexrail1 is a line voltage bendable single circuit track system. The rail is ordered as a four or eight foot section to be bent in the field as needed or used as a straight section.
Materials:	Flexrail1 is a polycarbonate extrusion with an aluminum core and three copper bus wires. Each rail also includes two matching polycarbonate endcaps.
Electrical:	1 circuit, rated 2400w. 3 wires (one hot, one neutral & one ground). 120/240V 60Hz single phase, 20 amps.
Fixtures:	Flexrail1 utilizes low voltage, line voltage, compact fluorescent, metal halide and quick connect track heads and pendants. The Flexrail1 system uses HM1 style track heads as well as quick connect low voltage track heads and pendants in conjunction with the HM1-EN50 quick connect transformer adaptor.
Mounting:	Mounts to flat, suspended, or sloped ceilings. Use 2 HM1-X supports per 4 foot section and at least 3 per 8 foot section. Total number of supports dependant on application.
Finish:	Abrasion resistant platinum (PT) or bronze (BZ) paint finish.
Listing:	U.L. & C.U.L. listed. 5 year W.A.C. Lighting product warranty.

Specification Features
<ul style="list-style-type: none"> The suspension rods for Flexrail1 are field cuttable or extendable (96" max). Rods are available for most ceiling types. The HM1-EN50 quick connect transformer adaptor allows the use of any quick connect element on the Flexrail1 system. Quick connect transformer adaptors are ordered separately. Rail can be put together to any length desired. The use of the "I" connectors will be required when connecting sections of track. The total load of a Flexrail1 system can be up to 2400 watts. "Quick-Ship" item, always in stock and available for immediate shipment.

CATALOG NUMBER	TYPE
PROJECT	



FLEXRAIL1 STRAIGHT RAIL

MODELS HM1-T

Accessory Ordering Matrix				
Model	Part Number			Finish
<input type="text"/>	<input type="text"/>			<input type="text"/>
HM1	EC	BM	EN50	PT BZ

Ordering Example (model number – part number – finish): HM1-EC-BZ

Track Accessories

Flexrail1 End Cap HM1-EC- <i>color</i>		Bending Machine HM1-BM	
---	---	---------------------------	---

Description Extra end cap for Flexrail1. Ordered when doing multiple cuts of a long piece of rail. Available in Platinum (PT) or Bronze (BZ).	Description Optional tool used to make extremely smooth and consistent bends of rail. Two clamp brackets mount bending machine to table or similar flat surface. Angle indicators on bending machine help the user determine the proper amount of tension. <i>Note: No color options.</i>
--	--

Flexrail1 Quick Connect transformer adapter.* HM1-EN50- <i>color</i>	
---	--

Description Flexrail1 system transformer adapts all quick connect elements (track heads or pendants) for use with the HM1 system rail. The adaptor contains a threaded nipple for quick connect socket sets and also houses a 50 watt electronic transformer. One adaptor must be ordered for each quick connect element used on a system. Available in Platinum (PT) or Bronze (BZ).
--

*More information regarding the quick connect adaptor can be found on the HM1-EN50 spec sheet.